

WISI DXC 0924

FLEXSWITCH multiswitch 9 in 24, cascade



Description

The DXC 0924 cascable multiswitch is equipped with 8 satellite IF polarization input and 1 terrestrial input. They all could be forwarded to the corresponding trunk outputs and to other possible connected multiswitches and they could be switched to up to 24 subscriber outputs. Any commercial available DVB-S/S2 set-top-boxes as well as any TVs with integrated satellite receiver can be connected to this outputs. More than that, terrestrial DVB-T/T2, DAB+ or FM signals can be additionally inserted over the corresponding input connector and can be distributed to all connected multiswitches in cascade or any reception devices. The multiswitch itself and any preconnected multiswitches or LNB can be supplied over the DC input connector by using one of the external power supplies DXP 1812 or DXP 1830, depending on the requested power.

At a glance:

- Cascadable multiswitch for the distribution of 8 satellite polarisations and terrestrial signals
- Active terrestrial path to distribute DVB-T/T2, DAB and FM without an additional amplifier
- Pre-emphasis to compensate the cable loss at high frequencies
- Integrated SAT amplifier for low insertion loss
- High screening efficiency according to Class A
- Compact dimensions paired with installation friendly distance between the F-connectors
- Colour-coded inputs and outputs
- Compatible with all cascable DXC 09xx

WISI Communications GmbH & Co. KG

Wilhelm-Sihn-Str. 5-7
75223 Niefern-Oeschelbronn, Germany

Phone: + 49 7233 66-0, Fax - 350
E-Mail: export@wisi.de

Technical Modifications reserved. WISI cannot be held liable for any printing error. 11. Oktober 2024, 9:00 AM

Technical data**SAT-IF trunk**

Inputs SAT 8 pcs.

Outputs SAT 8 pcs.

Frequency range-SAT 950...2150 MHz

Through loss SAT 7 dB

Isolation SAT -SAT 30 dB typ.

Return loss SAT >10 dB

Terrestrial trunk

Inputs TERR 1 pcs.

Outputs TERR 1 pcs.

Frequency range TERR 47....862 MHz

Through loss TERR 5 dB

Isolation TERR - SAT 30 dB typ.

Return loss TERR >10 dB

Subscriber outputs

Outputs 8 pcs.

Frequency range 47...2150 MHz

TERR type Active

Insertion loss SAT 4...-1 dB

Insertion loss TERR 0 dB

Max. output level subscriber SAT 100 dBμV (IMA3 @ 35dB)

Max. output level subscriber TERR 90 dBμV (IMA3 @ 60 dB)

Return loss subscriber SAT >10 dB

Return loss subscriber TERR >10 dB

Control signal 13/18 V, 0/22 kHz, DiSeqC 1.0/2.0

Current consumption from receiver max. 50 mA

Connectors

F-Female 42 pcs.

Impedance 75 Ω

DC supply voltage F-Female

Color code VL = black; HL = green;
VH = red; HH = yellow**General data**

Operating voltage 15...20 V DC

Power consumption max. <3.5 W

Screening factor Class A, according to EN 50083-2

Operating temperature range -20...55 °C

Weight 1.1 kg

Dimensions (width x height x depth) 300 x 175 x 60 mm

Packaging data

Sales unit 1 pcs.

Dimensions (WxHxD) sales unit 318 x 185 x 65 mm

Packaging volume sales unit 3.9 dm³

Gross weight sales unit 1.25 kg

EAN 4010056768836

Article number 76883

Customs tariff number 85437090